

DATA SHEET

Detachable Battery Pack *BTR-08*


BTR-08

The Detachable Battery Pack, BTR-08 is used exclusively for Fujikura Arc Fusion Splicer, FSM-60S, FSM-60R, FSM-18S, and FSM-18R.

The battery is rechargeable, and to be charged by ADC-13, AC adaptor and DCC-14, charge cord.

SPECIFICATIONS

Model	BTR-08
Type	NiMH (Nickel Metal Hydride)
Output voltage	13.2V
Battery capacity	4.0Ah
Battery charger	Exclusive Battery charger, ADC-13 Battery charge cord, DCC-14
Expected battery cycle life	Max. 500 cycles
Battery capacity indicator	Available
Operating condition	-10 to +50 degree C / Non dew
Dimension, Weight	120W x 117D x 38H (mm), 0.77kg
Use for	FSM-60S, FSM-60R, FSM-18S, FSM-18R

USAGE CONDITION

- Performing a cycle of full discharge and full charge is recommended in a few months period, due to self-discharge characteristics of NiMH battery.
- The batteries shall be stored in full charge condition.

PERFORMANCE

No. of splicer operation (Splicing / tube heating)	Splicer model	BTR-08
	FSM-60S	160 cycles
	FSM-60R	90 cycles
	FSM-18S	150 cycles
	FSM-18R	90 cycles


**DCC-14
Charge cord**

Specifications and descriptions are subject to change without prior notice.

Fujikura Ltd.

1-5-1, Kiba, Koto-ku, Tokyo 135-8512, Japan

 Phone : +81-3-5606-1164 Fax : +81-3-5606-1534 <http://www.fujikura.co.jp>
Fujikura Asia Ltd.

460, Alexandra Road, #22-01 PSA Bldg., Singapore 119963

 Phone : +65-6-271-1312 Fax : +65-6-278-0965 <http://www.fujikura.co.sg>
Fujikura Europe Ltd.

C51 Barwell Business Park, Leatherhead Road, Chessington, Surrey KT9 2NY, UK

 Phone : +44-20-8240-2000 Fax : +44-20-8240-2010 <http://www.fujikura.co.uk>
AFL Telecommunications

260, Parkway East, Duncun, SC29334, USA

 Phone : +1-800-235-3423 Fax : +1-800-926-0007 <http://www.afttele.com>